

Cordless Pruning Saw DUC101 100 mm (4") UC100D 100 mm (4")



makite photo: DUC101 **Automatic chain lubrication** photo: DUC101 photo: UC100D

Charging Time

12V/max [UNTHOM#JON]	BL1016 1.5Ah 197393-5	BL1021B 2.0Ah 197396-9	BL1041B 4.0Ah 197406-2
Past Charging DC10SB	22 min	30 min	60 min
DC10WD	50 min	70 min	130 min

18V	BL1815N 1.5Ah 196449-1	BL1820B 2.0Ah 197254-9	BL1830B 3.0Ah 197599-5	BL1850B 5.0Ah 197280-8	BL1860B 6.0Ah 197422-4
Fast Charging DC18RC	15 min	24 _{min}	22 min	45 min	55 min
DC18SD	30 min	45 min	60 min	110 min	130 min

DUC101

55 mL (1.9 USoz) Front : 4.6 m/s²

Rear: 4.0 m/s² w/o Battery: 357 x 90 x 232 mm (14 x 3-1/2 x 9-1/8")

w/BL1815N/BL1820B: 394 x 90 x 245 mm (15-1/2 x 3-1/2 x 9-5/8")

1.6-2.0 kg (3.5-4.4 lbs.)

UC100D

55 mL (1.9 USoz) Front : 4.8 m/s²

Rear: 4.1 m/s² w/o Battery: 350 x 90 x 215 mm (13-3/4 x 3-1/2 x 8-1/2")

w/BL1016/BL1021B: 383 x 90 x 220 mm (15-1/8 x 3-1/2 x 8-5/8")

100 mm (4")
Type: 80TXL
Pitch: 0.325"
Gauge: 1.1 mm (0.043")
8.0 m/s (480 m/min) (1,570 FPM)
T00 mm (4")
Type: 80TXL
Pytch: 0.325"
Gauge: 1.1 mm (0.043")
8.0 m/s (480 m/min) (1,570 FPM)

W/BL1830B / BL1840B / BL1850B / W/BL1041B: 398 × 90 x 226 mm BL1860B: 408 x 90 x 249 mm (15-5/8 x 3-1/2 x 8-7/8")

nt : Saw chain, Guide bar, Guide bar case, Round file (country-specific),

Accessories

Holster set

Part No. 1911R0-4

Storage and carrying of the machine









Guide bar 4 set

Part No. 1910W0-3

Trakita.

Type: 80TXL Length: 100 mm (4") Gauge: 1.1 mm (0.043)

Saw chain 4 set

Type: 80TXL

Number of links: 26 Pitch: 0.325"

Part No. 1910V6-4

Gauge: 1.1 mm (0.043)

Cordless Pruning Saw

DUC101 100 mm (4")

The weight may differ depending on the attachment(s), including the battery cartridge. The lightest and heaviest combination, according to EPTA-Procedure 01/2014, are shown in the table. Items of standard equipment and specifications may vary by country or area.

Makita Singapore Pte Ltd

7, Changi South Street 3, Singapore 486348 Phone: +65-6546-8700 Fax: +65-6546-8711 Email: msgproduct team@makita.com.sgWebsite: www.makita.com.sg Facebook: www.facebook.com/MakitaSG









Chain oil (country-specific), Battery, Charger

PRINTED IN SINGAPORE

DUC101

Battery: BL1830B



UC100D



Battery: BL1021B













Compact and lightweight BL motor





eXtreme Protection Technology

Automatic chain lubrication



minimizes the chance that saw chain will stall due to forgetting to supply chain oil.

New Tool-less change and tension adjustment of saw chain





- Simply loosen and re-tighten the lever to automatically adjust the tension of saw chain.
- This easy-to-operate large lever is designed to be pulled up and turned easily.